

IMPORTANT INFORMATION

Azuma® Maxi Solo/Duet

WL479/WL480/WL481/WL482

INSTALLATION INFORMATION



1. **NB:** Ensure electrical supply is isolated before fitting and/or making any electrical connections. Luminaires should be disconnected from the mains supply before any High Voltage Insulation tests are carried out.
2. Make provision for fixing holes with centres of 50mm (other fixing hole positions are available).
3. **NB:** The Azuma Maxi Solo can be positioned for either uplighting or downlighting.
4. Make an access hole for the mains/dimming cabling in the centre of the fixing holes (other cable entry holes are available).
5. Bring the mains/dimming cabling through the access hole allowing enough cable to reach the Connector Block.
6. Remove the two M4 Screws holding the Mounting Plate to the Gear Housing, remove the Mounting Plate and retain the Screws.
7. Disconnect the Earth Cable from the Earth Tab on the Mounting Plate.
8. Fix the Mounting Plate to the mounting surface using screw fixings suitable for both the type of mounting surface and the weight of the luminaire.
9. Offer the luminaire up to the Mounting Plate.
10. Make the mains/dimming connections to the Connector Block according to the information on the Mounting Plate.
11. Re-connect the Earth Cable to the Earth Tab.
12. Align the holes on the Gear Housing with the holes in the Mounting Plate and fix using the two M4 Screws previously removed.
13. Reconnect the electrical supply and test the installation.