

IMPORTANT INFORMATION

Wallwasher Grid Light IM290



1. *Ensure electrical supply is isolated before fitting and/or making any electrical connections. Luminaires should be disconnected from the mains supply before any High Voltage Insulation tests are carried out.*
2. Remove the ceiling tile in required position.
3. Insert a length of T-Bar across the aperture to support the Wallwasher on all sides.
4. The luminaire width is 102mm, set the additional length of T-Bar accordingly.
5. Feed the Mains/Dimming cable through the aperture.
6. Make the Mains/Dimming connections according to the information on the Driver.
7. Angle the Wallwasher through the aperture and drop it down so that it is sitting securely on the T-Bars.
8. Cut the ceiling tile removed to fit the remaining aperture.
9. Reconnect the electrical supply and test the installation.